


RJ45 verloopkabels VPEB

Verloopkabel RJ45 ↔ 9-subD (TM-H / PM32)

Noot: PM32 gebruikt alleen RJ45 aders 2, 4, 5 en 7

1	NC
2	GND
3	C+ (A)
4	D- (B)
5	D+ (A)
6	C- (B)
7	GND
8	NC




1	NC
2	D+ (A)
3	D- (B)
4	NC
5	GND
6	NC
7	C- (B)
8	C+ (A)
9	PWR

9-subD female

Verloopkabel RJ45 (U485J) ↔ 3 polig (OC32/OM32)

1	NC
2	GND
3	C+ (A)
4	D- (B)
5	D+ (A)
6	C- (B)
7	GND
8	NC




1	D- (B)
2	D+ (A)
3	GND

Verloopkabel RJ45 ↔ 9-subD (CAN)

Let op: subD male en female zijn elkaars spiegelbeeld

1	PWR
2	GND
3	NC
4	CANH
5	CANL
6	NC
7	GND
8	PWR



1	NC
2	CANL
3	GND
4	NC
5	NC
6	NC
7	CANH
8	NC
9	PWR

9-subD